

## Savox SILENTA®

# A-COM 2BT

**COMMUNICATION HEARING PROTECTOR** 

HEAR BETTER / SEE FURTHER / DECIDE FASTER



#### Wireless Bluetooth Connection - can be paired with two devices

This hearing protector includes two separate Bluetooth units in left and right earcup:

The Bluetooth unit in left earcup is for Motorola two-way radio. It supports PTT-functionality over Bluetooth with Motorola e-series radios with HKVN4465 licence activated.

The Bluetooth unit in right earcup is for mobile phone. If your phone supports the A2DP Bluetooth profile and has a music player feature, you can also use the phone to play music with the hearing protector.

#### The most important features are the safety features

The voice/sound will always be heard through Motorola radio even though the other device is active. This is an important feature of safety.

PTT- talk on shell enables to communicate by pressing the rotary switch on the left ear cup. It is mechanically reliable and easy to use even when wearing work gloves.

If you are having a mobile phone conversation (or the other device is active) and you push the Motorola PTT rotary switch, your voice will be heard in both devices. This is also an important feature of safety.

## SILENTA® A-COM 2BT

COMMUNICATION HEARING PROTECTOR







#### **BLUETOOTH®**

- Qualified Bluetooth device, for wireless connection to a mobile phone or communication radio
- Wireless transmission range approximately 10 m
- A2DP, HFP ja HSP profiles and has a stereo music player feature
- · Push-To- Talk on shell
- · Easy to connect by simple pairing feature

#### **HIGHLIGHTS**

- Unique casting technique to protect the electronics
- Low battery warning and automatic switch off after 5 hours
- Robust flex-boom mic with excellent background noise cancellation
- Gel filling and padded headband and spacious cups for the maximum user comfort
- · Foldable, easy to transport and store

#### MECHANICAL

Weight	454 g
Material	Cups (ABS) Headband (Stainless steel + PVC)
	Ear seals (PVC)

#### **HEARING PROTECTION CAPABILITIES**

SNR	33 dB
NRR	26 dB

#### **ELECTRICAL**

Power Supply	Rechargeable Li-on battery and charger
Operation time	100 h or 20h when Bluetooth active

## savox

### **SILENTA®**

Silenta Group Oy Länsiväylä 7 40700 Jyväskylä Finland Tel. +358 14 377 1522

E-mail: sales.silenta@savox.com / sales.emea@savox.com